



CONVERGE Pro 2 is the industry's most advanced professional audio DSP platform for conferencing and sound reinforcement applications. It outperforms in any size room, any audio environment, any application.

CONVERGE Pro 2 is optimized to work with the new Beamforming Mic Array 2 and DIALOG® 20 2-Channel Wireless Microphone System through its native connection.

Powerful Architecture

- + 12 Mic/Line inputs with AEC
- + Built-in VoIP – 2 lines +3 lines (license)
- + Built-in Telco with ClearEffect™ processing
- + Built-in USB for PC-based conferencing
- + Built-in Dante for networked audio
- + Reduced footprint and power consumption

Scalable Connectivity

- + Standalone and daisy-chained system
- + Stack up units up to 144 Mic/Line inputs (or 12 units)
- + Expansion bus “C-Link” with 64 channels
- + “P-Link” bus to connect 6 peripherals

Configuration & Management

- + New CONSOLE® software
- + Auto-discovery of devices
- + Matrix View for entire system
- + FlowView™ for visualized audio signal paths
- + System monitoring and troubleshooting

Audio Signal Processing

- + Next-gen Acoustic Echo Cancellation processing
- + Distributed Echo Cancellation® on every mic input
- + Noise Cancellation with Adaptive-Ambience
- + Acoustic Intelligence with faster convergence
- + DARE™ feedback elimination
- + Advanced microphone gating

Any Application

- + VoIP/POTS conferencing
- + PC-based conferencing & Unified Communications
- + Sound Reinforcement applications
- + Dante™ for audio networking

Flexible Control Options

- + Dialer app for Windows, Mac, iOS, Android
- + Tabletop controller with touch panel
- + Wall controller with buttons
- + Web based controller
- + 3rd party control modules



VENUES

Boardrooms

Conference Rooms

Huddle Rooms

Training Rooms

Lecture Halls

Courtrooms

Auditoriums

Telemedicine Facilities

Functional Specifications

Unless otherwise specified, all measurements are performed with a 20Hz to 22kHz BW (no-weighting).

Specifications are applicable based on the SKU types.

MIC/LINE INPUTS & OUTPUTS

Inputs: Balanced audio inputs, 3.81mm Orange color Phoenix/Euroblock type male header, Push-on mini-terminal block

Outputs: Balanced audio outputs, 3.81mm Black color Phoenix/Euroblock type male header, Push-on mini-terminal block

Frequency Response:

20Hz – 22kHz @ +4dBu, +/- 0.5dBu

EIN (Equivalent Input Noise):

20kHz BW, max gain, $R_s = 150\Omega$, -126dBu

THD + N (Total Harmonic Distortion + Noise):

20Hz – 22kHz @ +4dBu, line level, 0.006%

20Hz – 22kHz @ -56dBu, mic level, <0.04%

Dynamic Range:

20Hz – 20kHz @ 0dB, >105dB

Crosstalk (Mic/Line):

Channel to Channel, stimulus at 20dBu to receptor at -56dBu, 1kHz, < -98dB

Input Impedance:

Balanced (line to ground), 2.2k Ω , 1%

Nominal Input Level:

Adjustable -56dB to 0dB, 7dB step coarse gain

Maximum Input Level:

-65dBu to 20dBu

Phantom Power:

48V, Impedance 6.81k Ω

Output Impedance:

Balanced (line to ground), 95 Ω , 1%

Output Level:

0dBu (Nominal), 20dBu (Max), -40dBu (Selectable)

USB AUDIO

Port Type: USB-B connector

Audio: Digital Audio, 2 x 2 bidirectional channels

Sample Rate: 48kHz

Sample Bit Depth: 24-Bit

Compatible:

USB 2.0

USB 3.0

TELEPHONE

Port Type: RJ11

Frequency Response:

- Mic/Line Input to Telephone Out: 250Hz – 3.4kHz, +/- 2dB, 4dBu
- Telephone In to Mic/Line Out: 250Hz – 3.4kHz, +/- 2dB, -15dBu

THD + N:

- Mic/Line Input to Telephone Out: <0.1% @ 4dBu
- Telephone In to Mic/Line Out: <0.3% @ -15dBu

Dynamic Range:

- Mic/Line Input to Telephone Out: >67dBu
- Telephone In to Mic/Line Out: >87dBu

REN:

Ringer Equivalent Number 0.2

Transhybrid Balance:

30dB (1kHz, all AC terminations)

VOIP

Port Type:

RJ-45, 10/100Mbps Ethernet Network, Auto Negotiation

Audio:

5 Lines (2 default + 3 lines through License), each line supporting 1+5 calls

Sample Rate: 24kHz

Sample Bit Depth: 24-Bit

Codec:

- G.711 uLaw
- G.711 ALaw
- G.722

ETHERNET

Port Type:

RJ-45, 10/100Mbps Ethernet Network, Auto Negotiation

IP address: IPv4 (IPv6 upgradeable)

DANTE™ AUDIO

Port Type: RJ-45 Gigabit Ethernet connectors for Primary and Secondary Ports

Audio: Digital Audio, 16 x 16 bidirectional channels

Sample Rate: 48kHz / 96kHz

Sample Bit Depth: 24-Bit

AMPLIFIER OUTPUT (applicable to 48T SKU)

Speaker Output Port: Dual binding posts

Audio: 2 Channels

Output Power: 10W Max, 8 Ω load

Frequency Response:

20Hz – 22kHz @ +10dBu, +/- 0.5dBu

THD + N: 20Hz – 22kHz @ +10dBu, 1W, <0.3%

Dynamic Range:

20Hz – 22kHz @ 20dB, >102dB,

with 20kHz digital low pass filter

Crosstalk:

Channel to Channel, stimulus at 20dBu,

10W output to receptor 8 Ω load, 20Hz – 22kHz, < -70dB

C-LINK EXPANSION BUS

Ports Type: RJ-45 (Cat5e or Cat6)

C-Link In & Out: Proprietary Expansion Bus

Audio: 64 Expansion channels

Cable: Solid core, factory terminated Cat 5e or 6 cable

Distance: Up to 150 Ft (45M)

P-LINK PERIPHERAL BUS

Ports Type: RJ-45 (Cat5e or Cat6)

P-Link In & Out: Proprietary Peripheral Bus

PoE In:

- P-Link In Port
- PoE IEEE802.3AF

Audio: Up to 3 Beamforming Microphone Array 2 units + up to 3 DIALOG 20 Wireless Receiver units

Cable: Solid core, factory terminated Cat 5e or 6 cable

Distance: Up to 200 Ft (60M)

RS232

Port Type: DB9 Female

Settings: 9600/19200/38400/57600/115200 Baud;

Serial Echo; Flow Control

Support: Serial commands

GPIO

Port Type:

5.08mm Green color Phoenix/Euroblock type male header

Support: Control, Status, Variable Voltage Control

Power Pin: 5V DC @ 350mA Power Source

Pin 1 to 4:

Open Collector Outputs: 40VDC @ 250mA
Active Outputs (Source/Sink): 5VDC @ 25mA
Logic Inputs: 40.2k Ω pull up
Variable Voltage Control Inputs: 5VDC max

Ground Pin: GND

USB CONTROL

Port Type: USB-B connector

Location: Front Panel

Compatible:

- USB 2.0
- USB 3.0

LEDs

Location: Front Panel

Status LED:

- Off: Unit still initializing
- Blue - Fast Blinking: Stack Syncing in progress
- Blue - Slow Blinking: Unit not configured
- Blue - Solid: Configured unit
- Red - Fast Blinking: Stack Sync error

Locate LED:

Blue - Blinking: Unit "Locate" command received

Power LED:

Blue - Solid: Unit is powered on

TOUCH SENSOR

Sensor Type: Capacitive Touch Button

Location: Front Panel

POWER & THERMAL

Port Type: AC Inlet

Mains Voltage: 100-240V AC, 50/60Hz

Power Consumption: 50 Watts Typical

Thermal: 170 BTU/Hr Typical

Operating Temperature:

14°F/-10°C to 104°F/40°C Ambient Temperature

DIMENSION & WEIGHT

RU size: 1 RU

Width x Depth x Height:

- Without rack-ears: 17 x 10.73 x 1.72in or 43.2 x 27.3 x 4.4cm
- With rack-ears: 19 x 10.73 x 1.72" or 48.3 x 27.3 x 4.4cm

Unit Weight: 9.3 lbs (Approximately)

Shipping Weight: 13.8 lbs (Approximately)

PACKAGE (as applicable based on SKUs)

Power Cord: 6 Ft (1.8M), Grounded, Qty 1

Input Connectors:

Terminal Block Connector, 3 Position (Orange), Qty 12

Output Connectors:

Terminal Block Connector, 3 Position (Black), Qty 8

GPIO Connector:

Terminal Block Connector, 6 Position (Green), Qty 1

C-Link Cable:

RJ-45 To RJ-45 Cable, 18 Inches (0.45M), Qty 1

Telephone cable: 12 Ft (3.6M), Qty 1

VoIP Cable: RJ-45 To RJ-45, 7 Ft (2M), Qty 1

USB Cable: USB Type A to Type B, 6 Ft (1.8M), Qty 1

Rack Ears: Pre-installed, Qty 2

Screw/Washer Kit: Rack Decor, Qty 4

PART NUMBERS

| Part Number | Product |
|----------------|-----------------------|
| 910-3200-001 | CONVERGE Pro 2 128 |
| 910-3200-001-D | CONVERGE Pro 2 128D |
| 910-3200-002 | CONVERGE Pro 2 128T |
| 910-3200-002-D | CONVERGE Pro 2 128TD |
| 910-3200-003 | CONVERGE Pro 2 128V |
| 910-3200-003-D | CONVERGE Pro 2 128VD |
| 910-3200-005 | CONVERGE Pro 2 48T |
| 910-3200-004 | CONVERGE Pro 2 120 |
| 910-3200-101 | CONVERGE Pro 2 128SR |
| 910-3200-101-D | CONVERGE Pro 2 128SRD |

SALES AND INQUIRIES

North America

Tel: +1 801.975.7200

TollFree: +1 800.945.7730

TechSales: +1 800.705.2103

Fax: +1 801.303.5711

sales@clearone.com

Europe

Tel: +1.800.945.7730

global@clearone.com

Middle East

Tel: +1.800.945.7730

global@clearone.com

Asia Pacific

Tel: +1.800.945.7730

global@clearone.com

Other Regions

Tel: +1.800.945.7730

global@clearone.com

Other product names may be registered trademarks of their respective owners who do not necessarily endorse ClearOne or ClearOne's products. All rights reserved. Information in this document subject to change without notice. © 2016 ClearOne.